

02-61

ATECH TECHNOLOGY CO., LTD.

DESIGN SHEET

DS-001

CUSTOMER	PART NUMBER	REV	CONSTRUCTION											SCHEMATIC DRAWING
新林	ATC-02-016													
BOBBIN: SMD-BASE-014. 5/6 PINS BS-505-05														
CORE: RJD 2x3.5x1.8. Q4 (2x4) FC-BL020103-01														
GAP: ☒														
TAPE: ☒														
ASSEMBLY: CORE 組合時, 於 BASE 上先 些 GL-014 膠. 燒乾固定後, 再繞線														
FRAME (CLIP): 纏腳焊錫固定.														
PIN#5 INDICATOR: PIN5 剪除														
TAP WID Mm	TAP LYR	WID	STR	END	CW/ CCW	WIR SIZ	COA	TUR	CRE PAG	DEN LSN	SIDE WALL			
		W1	1	6	順	0.14	1/2W	7		密				
		W2	3	4	順	0.14	1/2W	7		密				
		W3												
		W4												
		W5												
		W6												
		W7												
		W8												
												REMARKS		
												1. 繞線時, 注意相位, 不可繞錯. 2. PIN5 剪除. 3. 繞線時注意, 線的出入位置. 請參考 TOP VIEW. 4. 繞 W1, W2 時須先從 PIN6 及 PIN4 起繞. 由 CORE 底部循序往上繞. PIN1 及 PIN3 繞尾.		
												PAGE / OF / REV.		
												Design Engineer: Shiah		