

CUSTOMER		PART NUMBER		REV		CONSTRUCTION							SCHEMATIC DRAWING	
矽晶行		ATC-03-002				TAPE 1 1/4 TS SEC#2, SEC#3 SEC#4, SEC#5 SEC#6, SEC#7 SEC#8 W1 2 SEC#1 W1 双线圈 8' 10 4' 6 1' 3								
BOBBIN: BB-UI15-02													BOTTOM VIEW PIN LOCATION	
CORE: FC-UI15-02														
GAP: /														
TAPE: BD21														
ASSEMBLY: CORE 组合後用治具固定再用 9204 美胶														
FRAME(CLIP): FM-UI15-01														
PIN#1 INDICATOR:														
TAP WID Mm	TAP LYR	WID	STR	END	CW/CCW	WIR SIZ	COA	TUR	CRE PAG	DEN LSN	SIDE WALL	REMARKS		
		W1	1	3	反	0.16	24	24		密		1. 繞 W1, W2 時, BOBBIN PIN#1 朝外。 2. 繞 W3 時, BOBBIN 反插, PIN#1 朝內。 3. W1, W2 繞 SEC#1 4. W3 繞 SEC#2 開始繞 ① SEC#2 繞 25 TS ② SEC#3 繞 25 TS ③ SEC#4 繞 25 TS ④ SEC#5 繞 25 TS ⑤ SEC#6 繞 25 TS ⑥ SEC#7 繞 25 TS ⑦ SEC#8 繞 25 TS 5. 繞 W3 時繞完後繞 3A 2		
双线圈		W2	4	6	反	0.16	24	24		密				
		W3	8	10	順	0.04	P180 GZ	1800		密				
14.3	1 1/4	W4												
		W5												
		W6												
		W7												
		W8												
PAGE OF REV.														
Design Engineer: Willie														

REMARK 6: 繞完線後, 須由 BOBBIN 側用線端拉回夾在 PIN#1 10.

REMARK 7: 繞完線後貼 BOS1 14.3 on TAPE 1 1/4 TS. 重疊有倒逆兩側不可有斜角, 否則 L 值不良.

REMARK 8: 繞完線後, 加上外殼 (C-01), 插入 I core, 再放上 U core 後

用治具夾緊固定起來 4 隻 62-014 螺絲固定

