

CUSTOMER	PART NUMBER	REV	CONSTRUCTION											SCHEMATIC DRAWING			
碩磁	ATC-03-035																
BOBBIN:	BB-EFD15-03													BOTTOM VIEW PIN LOCATION			
CORE:	PC-EFD15-02															REMARKS	
GAP:	有磨的在PIN1端																
TAPE:	3M#1350 9mm 3M#1350 4.5mm																
ASSEMBLY:	組裝後金口外圍用 3M#1350, 4.5mm膠布包2Ts																
FRAME(CLIP):	含浸前將鐵口往 PIN1側推																
PIN#1 INDICATOR:	BOBBIN 缺口																
TAP WID Mm	TAP LYR	WID	STR	END	CW/ CCW	WIR SIZ	COA	TUR	CRE PAG	DEN LSN	SIDE WALL						
雙線		W1	3	4	反	0.23	2	UBW	15		密繞						
		W2	4	5	反	0.23	2	UBW	15		密繞						
		W3	1	2	反	0.23	2	UBW	3		密繞						
		W4	6	10	順	0.05	2	UBW	1211		密繞						
3M#1350 9mm	→	W5									密繞						
		W6									密繞						
		W7									密繞						
		W8									密繞						
REMARK:												1. 繞W1, W2, W3時BOBBIN PIN#1朝外。 2. 繞W4時BOBBIN PIN#1 朝內, 跨SEL須走線溝。 3. 繞W4時, SEC#3, SEC#4 各繞404Ts, SEC#2繞 403Ts。 4. 測試時確認鐵口有 推往PIN1側。					
PAGE / OF /												REV.					
Design Engineer:																	
willie																	

REMARK:

5. 線包外層膠布結束於BOBBIN側面
6. 成品PIN#8剪除。
7. 整顆真膠含浸