

CUSTOMER		PART NUMBER		REV		CONSTRUCTION						SCHEMATIC DRAWING			
R&K		ATC-03-055													
BOBBIN: BB-EE1905-07														BOTTOM VIEW PIN LOCATION	
CORE: FC-EE1905-09															
GAP: ORIGINAL															
TAPE: 3M#1350															
ASSEMBLY: Core 組合時有GAP的 在 pin#1 側) 外包 3M#1350 12.5mm															
FRAME(CLIP): 2TS															
PIN#1 INDICATOR: DOT															
TAP WID Mm	TAP LYR	WID	STR	END	CW/CCW	WIR SIZ	COA	TUR	CRE PAG	DEN LSN	SIDE WALL	REMARKS			
		W1	4	2	順	0.17	2UEW	112		密		1. 繞 W1, W3 時 BOBBIN pin#1 朝外, 繞 W2 時 BOBBIN pin#1 朝內 銅箔 (厚度 0.05mm) 83mm 2. 銅箔 (厚度 0.05mm) 83mm 48mm TAPE 1250 11mm 0.17mm 銅箔 (注意不可錯放 TAPE, 以免 short)			
9.5	2	W2	5	8	順	0.65	TEX-E	8		密					
9.5	2	W3	2	1	順	0.17	2UEW	112		密					
9.5	2	W4	引	線	至	pin#3	結	尾							
9.5	2	W5													
9.5	2	W6													
9.5	2	W7													
9.5	2	W8													
5. 2. 1. 2. 3. 4. 5. 6. 7. 8. 9. 10. 11. 12. 13. 14. 15. 16. 17. 18. 19. 20. 21. 22. 23. 24. 25. 26. 27. 28. 29. 30. 31. 32. 33. 34. 35. 36. 37. 38. 39. 40. 41. 42. 43. 44. 45. 46. 47. 48. 49. 50. 51. 52. 53. 54. 55. 56. 57. 58. 59. 60. 61. 62. 63. 64. 65. 66. 67. 68. 69. 70. 71. 72. 73. 74. 75. 76. 77. 78. 79. 80. 81. 82. 83. 84. 85. 86. 87. 88. 89. 90. 91. 92. 93. 94. 95. 96. 97. 98. 99. 100.												PAGE 1 OF 1 Design Engineer: Kevin		REV. A	

T3 貼完後 再用上述材料包 IT, 需重疊 但不可 short. 引線需至 pin#3 結尾 (重疊處在底部)

3. 成品需校正合浸
4. 各引線在 BOBBIN 正面不得外露