

CUSTOMER		PART NUMBER		REV	CONSTRUCTION							SCHEMATIC DRAWING	
Bourns		CTA41303MA SM536-1EL											
BOBBIN: 2334130A92													
CORE: >03130951V													
GAP:													
TAPE: Super 10 1.6mm 3M#74 2.9mm 3M#56 2.9mm													
ASSEMBLY: CORE組時有GAP在 PIN 1.外圍包3M#56 2.9mm膠													
FRAME(CLIP): 布2Ts.並夾6桌 G2-014 燒乾固定													
PIN#1 INDICATOR: PIN#1 白桌													
TAP WID Min	TAP LYR	WID	STR	END	CW/ CCW	WIR SIZ	COA	TUR	CRE PAG	DEN LSN	SIDE WALL	REMARKS	
双線	3	W1	1	4	順	0.14	2	順	Super 10 1.6mm	密			1.繞2s, 2s, 2s, 2s時 PIN#1朝外順繞 2.繞2s, 2s時PIN#1 朝內反繞 3.繞線要平整, 2s, 2s 結束時要拉直角 否則線包會太厚
		W2	2	5	順	0.14	2	順	兩端各2Ts	密			
双線	3	W3	10	7	反	0.22	2	順	Super 10 1.6mm	密繞			
双線	3	W4	9	6	反	0.22	2	順	兩端各6Ts	拉直角			
双線	2	W5	1	4	順	0.14	2	順	Super 10 1.6mm	密			
双線	2	W6	2	5	順	0.14	2	順	兩端各2Ts	密			
双線	2	W7											
双線	2	W8											
PAGE 1 OF 1 Design Engineer: Wille											REV. A		

4. 需RoHS型程 5. Marking需用綢印