

CUSTOMER		PART NUMBER		REV	CONSTRUCTION										SCHEMATIC DRAWING									
AMBIT		CTP30801KA																						
BOBBIN:		BB-EL0802-14																						
CORE:		LM-EL08-05																						
GAP:																								
TAPE:		3M#1350W PPI#7010																						
ASSEMBLY: 1*1共9片, 組合後, 在PIN#1端插入MX-024. 用膠帶固定															BOTTOM VIEW PIN LOCATION									
FRAME (CLIP): INSULATOR: MX-024																								
PIN#1 INDICATOR: 黑印印在LABEL上																								
TAP WID mm	TAP LYR	WID	STR	END	CW/ CCW	WIR SIZ	COA	TUR	CRE PAG	DEN LSN	SIDE WALL	REMARKS 1. 繞W1時, BOBBIN PIN#1 朝外 繞W2時, BOBBIN反插, PIN#1朝內 2. 插片時, 腳(腹部或杯 緣溝)那一面放桌面. 第一片鏤片自BOBBIN PIN#3,4那邊插入. 3. 內層TAPE 1/2 TS, 重疊在下方 外層TAPE 1/2 TS, 重疊在上方 貼外層TAPE前貼上LABEL.												
PPI# 7010 10.2mm	1 1/2	W1	2	1	順	0.045	P180 G1/F	1080	1350W 1.6mm 5TS在 PIN#4 那端	密														
PPI# 7010 10.2mm	1 1/2	W2	4	3	=	0.045	P180 G1/F	1080	1350W 1.6mm 5TS在 PIN#1 那端	=														
		W3																						
		W4																						
		W5																						
		W6																						
		W7																						
PAGE 1 OF 1 REV. B																								

REMARK 4: 裝 INSULATOR 須左右對齊, 緊靠鐵芯, 用膠帶固定, 不可鬆動。

REMARK 5: LABEL 要打桌, 貼在腹部。