

CUSTOMER	PART NUMBER	REV	CONSTRUCTION	SCHEMATIC DRAWING								
ASKEY	ATS-42A											
BOBBIN:												
CORE: CORE EP-13, TL-10. (2通)												
FC-EP13-42												
GAP:												
TAPE:			BOTTOM VIEW PIN LOCATION									
ASSEMBLY: CORE 組合時, 鏡面要乾淨.												
GAP 在 PIN I. 外引 3M#56 8mm TAPE												
FRAME (CLIP): 2 Ts												
PIN#1 INDICATOR:												
黑文印在 LABEL 上												
TAP WID Mm	TAP LYR	WID	STR	END	CW/ CCW	WIR SIZ	COA	TUR	CRE PAG	DEN LSN	SIDE WALL	REMARKS 1. 繞 W₁, W₂ 時, BOBBIN PIN I 朝內 2. 繞 W₃ 時, BOBBIN PIN I 朝外 3. 繞線前須先在 BOBBIN 上貼 3M#56, 7.9mm IT 重疊部分須超過 3mm 4. CORE 組合後, 須於 BOBBIN 中 CORE 處夾 6 支 GL-04 特乾膠
3M#56	2	W1	10	7	順	0.15	2	45	SUPER H/0 1.6mm 2Ts 在兩面	層數 層數		
7.9mm	2	W2	1	4	反	0.15	2	90	SUPER H/0 1.6mm 4Ts 在兩面	密		
3M#56	2	W3	10	7	順	0.15	2	45	SUPER H/0 1.6mm 2Ts 在兩面	密		
7.9mm	2	W4										
3M#56	2	W5										
7.9mm	2	W6										
3M#56	2	W7										
7.9mm	2	W8										
PAGE / OF / REV.												