

CUSTOMER		PART NUMBER		REV	CONSTRUCTION								SCHEMATIC DRAWING	
		CTP019001A												
BOBBIN:		BB-BE1905-01												
CORE:		LM-EE19-01												
GAP:		2 mil NOMEX 2 边												
TAPE:		3M #1350W											BOTTOM VIEW PIN LOCATION	
ASSEMBLY:		全巨对插共30片 加GAP. 外包 5.5mm TAPE 2TS												
FRAME (CLIP):														
PIN#1 INDICATOR:		下方白点												
TAP WID mm	TAP LYR	WID	STR	END	CW/ CCW	WIR SIZ	COA	TUR	CRE PAG	DEN LSN	SIDE WALL	REMARKS		
18.5	2	W1	3	1	顺	0.11	3	UEW	1400			1. 绕 W1 时 BOBBIN PIN#1 朝外; 绕 W2 时 BOBBIN 反插 PIN#1 朝内. 2. 内层 TAPE 包 5 圈要包好, 否则 HT 不良.		
18.5	2	W2	6	4	逆	0.11	3	UEW	1460					
		W3												
		W4												
		W5												
		W6												
		W7												
REMARK: 3. 插端子时要塞一电 10 mil NOMEX, 将端子塞紧。 4. 缠脚同 ATS-003 绕 3 圈。												PAGE 1 OF 1 REV. C		