



1. TOTAL DCR : 20 OHM MAX.
2. OFF HOOK INSERTION LOSS (@1KHZ) : SINGLE FILTER : 0.5dB MAX.  
WITH 5 FILTERS : 1dB MAX.
3. OFF HOOK INSERTION LOSS DISTORTION  
(@200HZ~3.4KHZ) : SINGLE FILTER : 0.5dB~-1dB  
WITH 5 FILTERS : 2.5dB~-1.5dB  
(@3.4KHZ~4KHZ) : SINGLE FILTER : 1dB~-1.5dB  
WITH 5 FILTERS : 3.25dB~-2dB
4. RETURN LOSS : PHONE PORT (@SRLL) = 13dB MIN.  
(@ERL) = 9dB MIN.  
(@SRLH) = 3dB MIN.  
LINE PORT (@SRLL) = 12dB MIN.  
(@ERL) = 10dB MIN.  
(@SRLH) = 5dB MIN.
5. LONGITUDINAL BALANCE (@200HZ~1KHZ) : 65dB MIN.  
(@1KHZ~3KHZ) : 56dB MIN.
6. ADSL FREQUENCY REJECTION (@25KHZ~2.2MHZ) : 21dB MIN.

|           |             |            |      |         |       |                                                                                                                      |                     |        |              |
|-----------|-------------|------------|------|---------|-------|----------------------------------------------------------------------------------------------------------------------|---------------------|--------|--------------|
|           |             |            |      |         |       | <div><div><div>Atech®</div><div>Atech Technology Co., Ltd.</div><div>TEL:02794-6667 FAX:02794-8004</div></div></div> | TITLE<br>SPLITTER   |        |              |
| A         | SPEC.       | 12/02/2004 | BART | MICHAEL | SUEDY |                                                                                                                      | DWG. NO.<br>ATF061A |        |              |
|           | RELEASE     | 05/28/2004 | PAIR | PAIR    | SUEDY |                                                                                                                      | UNITS:<br>M/M       | SAFETY | SHEET 1 OF 1 |
| NDI       | DESCRIPTION | DATE       | BY   | CHK     | APPD  |                                                                                                                      |                     |        |              |
| REVISIONS |             |            |      |         |       |                                                                                                                      |                     |        |              |